

## EagleLight LED 16-Watt PIR Motion Sensor Lights

PIR's 16-watt LED motion sensor lights are energy efficient LED lights with built in motion sensor light switch. PIR LED light bulbs come with 2 adjustments. One to adjust the level of sensitivity of the motion sensor lights, the second adjusts the time delay before the LED light turns off.

This bulb is ideal for use in applications such as

- \* LED closet lighting
- \* LED stairway lighting
- \* balconies
- \* Kids bathroom lights (So you do not have to ask to turn off every 5 minutes)
- \* LED garage lighting

The PIR LED motion sensor lights come with a standard screw-in base for easy installation. You can adjust the time cycle from 5 seconds to 12 minutes and you can adjust the motion sensor's sensitivity to either function constantly or only in dimly lit conditions

- **Base Type:** E27 screw-in base
- **Brightness:** Cool White: 1500 lumens Warm White: 1200 lumens
- **Energy Consumption:** 16 watt
- **LED elements:** 15 LED's
- **Voltage:** 90-240VAC
- **Color Temp:** Cool White: 6000K
- **Warm White:** 3000K
- **Beam Angle:** 140 degrees
- **Avg. Life:** 50,000 hours
- **Lens types:** Frosted
- **Diameter:** 2.5in (63.5mm)
- **Length:** 6.25in (158.75mm)
- **Weight:** 14 Ounces



### Photometrics

Product Number	Luminosity	Color Temperature	Beam Angle
T19-E27-16W15-MS-WW	~1000 Lumens	Warm White (3000K)	140 Degrees
T19-E27-16W15-MS-CW	~1500 Lumens	Cool White (6000K)	140 Degrees