

EagleLight LED 21-Watt PIR Motion Sensor Light Bulb

21-watt LED motion sensor light bulb with adjustable time delay. This bulb is ideal for use in applications such as closets, stairways, balconies, bathrooms, and garages. It has a standard screw-in base for easy installation. You can adjust the time cycle from 5 seconds to 12 minutes and you can adjust the motion sensor's sensitivity to either function constantly or only in dimly lit conditions. It is available in both Cool White and Warm White to better suit your application. The PIR LED motion sensor lights come with a standard screw-in base for easy installation. You can adjust the time cycle from 5 seconds to 12 minutes and you can adjust the motion sensor's sensitivity to either function constantly or only in dimly lit conditions

- **Base Type:** E27 screw-in base
- **Brightness:** Cool White: 2000 lumens Warm White: 1600 lumens
- **Energy Consumption:** 21 watt
- **LED elements:** 20 LED's
- **Voltage:** 90-240VAC
- **Color Temp:** Cool White: 6000K
- **Warm White:** 3000K
- **Beam Angle:** 140 degrees
- **Avg. Life:** 50,000 hours
- **Lens types:** Frosted
- **Diameter:** 2.75in (69.85mm)
- **Length:** 6.5in (165.1mm)
- **Weight:** 15 Ounces



Photometrics

Product Number	Luminosity	Color Temperature	Beam Angle
T22-E27-21W20-MS-WW	~1600 Lumens	Warm White (3000K)	140 Degrees
T22-E27-21W20-MS-CW	~2000 Lumens	Cool White (6000K)	140 Degrees