

5-Watt High Brightness Cree LED 35 Watt Replacement Bulb (E27)

This 5W LED MR16 bulb fits in a normal E26 or E27 standard screw socket and runs on 110-120VAC. This allow you to place a LED MR16 in a normal screw-in socket. Traditional track light MR16 bulbs run on 12VAC or 12VDC, this bulb operates on normal household 110-120 voltage. This bulb can replace up to a 35W conventional light bulb. This 5W LED MR16 produces 265 lumen. LED bulbs last much longer than halogen bulbs and burn much, much cooler. This MR16 has a stylish metal enclosure.

- **Bulb Shape:** MR16
- **Base Type:**E27
- **Brightness:**200-265 lumen
- **Energy Consumption:** 5 watts consumption
- **Replaces up to a:** 35watt incandescent bulb
- **Voltage:** 110-120VAC
- **Color:** Cool White, Natural White and Warm White
- **Color Temp:** Warm White: 3000K-3500K, Natural White: 4000K- 4500K, Cool White:6000K-6500K
- **Beam Angle:**45 degrees
- **Avg. Life:** 40,000 hours
- **Lens types:** clear
- **Diameter:** 2in (50mm)
- **Length:** 2.25in (57mm)
- **Weight:** 2 ounces (55g)



Photometrics			
Product Number	Luminosity	Color Temperature	Beam Angle
MR16-E27-5W3-WW	~200 Lumens	Warm White (3000-3500°)	45 Degrees
MR16-E27-5W3-NW	~235 Lumens	Natural White (4000-4500°)	45 Degrees
MR16-E27-5W3-CW	~265 Lumens	Day White (6000-6500°)	45 Degrees